

# danita S27F mobile antenna

27MHz CB antenna 57 cm.  $5/8\lambda$



Pre-tuned from factory to 27.2 MHz, but can be fine tuned in top of the antenna. Remove the top cap.  
Attention: When cap comes on, it influent on the SWR.  
The adjustment screw shall app. 6mm further down.



The cable is angled 90° from base for easy and professional look, under the vehicle roof.

Can be mounted from both inside and outer side.

FME/UHF adaptor included, so no soldering is needed.

## Specifications

### Electrical data:

CB band: (26.965-27.405 MHz)

Antenna type:  $5/8\lambda$

Whip material: Fiber stick

Band with: >500KHz

Impedance: 50  $\Omega$

Power: max. 100W

### Mechanical:

Length: Abt. 57cm

Weight: 490g

Cable: 4m RG58, 5mm

Cable end: FME

Add: Adaptor FME / UHF-PL259

### Mounting:

Mount from inside: 13,5mm hole

Mounting from outer side: 19mm hole

Spanner tool: 25mm. 5Nm.



Stock No.  
34149

